

CECT PDA Mobile Phone Manual

Chapter One basic information

1.1 Introduction

Thank you for purchasing the PDA color screen multimedia mobile telephone

please read all information carefully before getting started to install and use the Mobile. This would help you to make good use of this mobile and fully understand the functions of mobile and be easy to operate.

PDA color screen is aimed to design for GSM/GPRS network

PDA Color Screen Mobile complies with GSM/GPRS Technique regulations and it is certified by internal and external authorities.

Our company reserve the right to modify the content in this guide

1.2 for your safety

read these simple guidelines carefully. Breaking the rules may be dangerous or illegal.

Road safety comes first

Don't use a hand-held phone while driving .stop and park your vehicle safely before using your phone. .

Switch off in aircraft

Wireless devices can cause interference in aircraft. The use of mobile telephones in an aircraft is illegal .Please switch off your mobile before taking off the plane and please ensure the alarm clock should be closed when the mobile is turned off .

Switch off near blasting

To avoid interfering the process of blasting ,don't use the phone where you may read the sign of "Blasting Spot" or "Turn off your wireless". Observe restrictions and follow any regulations or rules.

Switch off near dangerous stuff

Don't use the phone at a refueling point Don't use near fuels or chemicals . switch the phone off in hospitals .

Switch the phone off near medical equipment .there may be a hazard associated with the operation of phones close to inadequately protected personal medical devices such as hearing aids and pacemakers .Don't put your phone on pacemakers which means not to put it in the pocket of clothes.

use your phone properly

The antenna is straight over your shoulder when you are talking to the phone. Don't touch the antenna if not necessary.

Emergency calls

Ensure the phone is switched on and in service. Enter the emergency number

and give your location .Do not end the call until told to do so .

1.3General Notice

1.3.1Don't hit ,shake or throw the phone violently to avoid being defective or catching fire

1.3.2

Don't place the battery ,phone and/or charger in the micro oven or and other high voltage equipments. This may result in damaging the circuit and catching fire

1.3.3

Do not use the phone in aexplosive and inflammable place .This may reslut in damaging the phone and causing fire .

1.3.4

Do not expose batteries to high temperatures,humidity or dusty. This may cause the faulty of the phone .

1.3.5

Place the phone where the children hardly reach it in order to made sure it won'thurt kids when they play it as a toy .

1.3.6

Do not plce the phone on an uneven and unstable .This may prevenr it from falling dwn to cause faulty or damage of the phone .

1.4Phone use Notice

1.4.1Your eyes would be in blind danger if the performance of some Please clean your eyes with water immediately (do not rub your eyes)and go to the hospital.

1.4.2Do not try to disassemble or modify the phone .It may result in phone damage,electric leakage and the circrit faulty.

1.4.3

Occasionally,Using the phone may affect the performance of some electric devices in the car . please do not use the phone under the circumstance for safety .

1.4.4Do not press the keys by sharp sruff such as needle or a head of a pen . It may cause of the phone damage and mis-opearition.

1.4.5Do not leave the phone if the antenna is broden .Or you will get hurt .

1.4.6

Do not leave the phone mear to magnetic objects such as magcad. Radiation of the phone may erase the storage information in software,saving card and credit card etc.

1.4.7

Keep small metsls such as pins away from the headthone.The lordspeaker is equipped with magnetism when it's working so that the small metals will be absorbed .This may hurt people or damage the phone.

1.4.8Keep the phone dry . Water and other types of liquids or moisture can overheat the phone and make the phone electric lectric leakage and be defective .

Battery use

1.5.1 Do not dispose of batteries in a fire! They will catch fire and be explosive.

1.5.2 Do not handle roughly the battery when installing. Or the batteries will leak, overheat, explode and catch fire.

1.5.3

Do not short-circuit the battery with a metallic object such as cable, pin, etc. And do not put the battery along with a metallic object such as necklace. Or the battery may leak, overheat, explode and catch fire.

1.5.4 Do not weld the battery terminals. The battery may leak, overheat, explode and catch fire.

1.5.5

Your eyes may be in danger when the battery liquid comes in. Please clean your eyes with water immediately {do not rub your eyes} and go to the hospital.

1.5.6 Do not disassemble or modify the battery which may leak, overheat, explode and catch fire.

1.5.7

Do not use or expose the battery beside a fire or heater or high temperature place, or the battery may leak, overheat, explode and catch fire.

1.5.8

Please stop and replace a new battery when the old one warms up, discolors or deforms when it's in use, charging or storage.

1.5.9

If the battery gets on the skin or clothes, it may hurt the skin. Please clean it with water and go to the hospital if necessary.

1.5.10

Take away the batteries from the bright fire if they smell weird or if the battery liquid leaks to avoid catching fire and being explosive.

1.5.11 Keep the batteries dry, or they may overheat, smoke and corrode.

1.5.12

Do not store the phone in hot areas. High temperatures can shorten the life of electronic devices, damage batteries, and warp or melt certain plastics.

1.5.13 Do not charge the battery over 24 hours.

1.5 Charger Use

1.6.1

Please charge with 220VAC

1.6.2 Short-circuiting the charger is not permitted, which may get an electric shock, smoke and damage the charger.

1.6.3 Do not use the charger if the cord is damaged, or it may catch fire and get an electric shock.

1.6.4

Please clean up the dust on the receptacle timely.

1.6.5 Do not leave a water container beside the charger to avoid overheating,

electric leakage and breakdown of the charger if the water spills out

1.6.6 The power cord should be removed from the receptacle if the charger touches the water and other liquid in order not to overheat, catch fire, get an electric shock and damage the charger.

1.6.7 Do not disassemble or modify the charger, or it may hurt people, get an electric shock and damage the charger.

1.6.8

Do not store the battery at the high-humidified place such as bathroom. It may get an electric shock, catch fire and damage the charger.

1.6.9 Do not touch the charger, cord and receptacle by your wet hands, which may get an electric shock.

1.6.10 Do not put an heavy stuff on power cord or modify the cord. It may catch fire and get an electric shock.

1.6.11

Take off the power cord from the receptacle before cleanliness and Maintenance.

1.6.12 Hold the charger with taking off the receptacle. The power cord may be damaged when pulling in result of catching fire and getting an electric shock.

1.6 Care and Maintain

1.7.1

Do not use the phone in high-humidified place such as bathroom if it is not water-proof and do not rain it, neither.

1.7.2 Clean up the phone, battery and charger with soft and dry cloth.

1.7.3 Do not clean the phone with alcohols, thinner or benzene solvents.

1.7.4

Contaminant on the receptacle may in result of bad connection, electric leakage so that the charging doesn't work. please clean the receptacle periodically

1/7

phone: Mobile Phone

always try to keep the phone the battery between 15°C and 25°C.

Please keep the phone far away the place where a common telephone, TV, radio and office equipment stay when it is in use in order not to affect the performance of using these devices and the phone.

battery

Store the battery be of sunlight and store it at cool and ventilated Place

The battery can be charged and discharged hundreds of times but it will eventually wear out. when the operating time (talk-time and standby time) is noticeably shorter than normal, it is time to buy a new battery.

Dispose of battery according to local regulations (e.g. recycling). do Charger

Do not charge the battery at the place that is shown as below: direct sunlight; external temperature is lower than 5 °C or higher than 40°C; humidity, dusty or shake violently (This may damage the charger); nearby TV, radio etc appliance (This may affect the video and audio performance)
Get started Technique parameter

2.1 Main Unit

Lithium battery

Model number PDA

Standard voltage 3.7v

Charging restriction Voltage 4.2v

Rated capacity mAh

Continuous Standby BE 80 hours about 70 hours ~

Continuous Talking BE 3 hours about 2 hours ~

Travelling charger

Input 100 ~ 240V 50/60HZ 200mA

2.2 SIM card (* some model PDA not support)

You have to insert the valid SIM card that is provided by your GSM system service supplier at first

Every information related network connection and your calling initial Records are recorded in the metal flat area of SIM Card. Besides, the names, phone numbers and SMS have recorded in the SIM card, which you save and receive them in the phonebook directory of SIM card. The SIM card can be taken out from your mobile phone and use in any GSM mobile phones. (The new mobile phone recognizes the SIM card automatically)

For prevent the information in the card from damage and lost, the metal flat area should not be touched as possible, and keep the SIM card far away the electricity and magnetism. Once the SIM card is damaged, you won't be able to access to a GSM network.

*Note: The phone must be switched off before taking out the SIM card. It is forbidden that the SIM card is inserted or taken out under the condition of plug in by external. Probably, the SIM card may be damaged.

2.2.1 Inserting and removing the SIM card

Usually The SIM card is hold by a card. Please ensure it will be released carefully before installing.

Switch off the mobile phone, remove the battery and other external power supplies

Insert the sim card into the simcard holder. Make sure that the sim Card is inserted properly and that the metal contact area on the card is

facing downwards.

When you need to remove the SIM card, please switch off the phone the SIM card holder.

2.2.2

Inserting and Removing The T-FLASH card

- The T-FLASH card is on the side of the mobile. The mobile and external power supplies must be switched off before installing and removing.
- Insert The T-FLASH card: Press the metal area of T-FLASH card downwards to the T-FLASH card slot until you can hear a sound "kaca", which means the card is in the place.
- Remove the T-FLASH card: Slightly press and the card and it may pop up, and then remove it.

2.3Diagram2

Battery

50%power will be charged into the battery at the initial. You can use the charger after unpacking it. The new battery needs to charge at least in 14 hours. When the power has been used up by the first time, (The mobile can't be switched on while the power is used up) fully recharge the battery again. Re-do the process as the first time using battery. Please note that a new battery's full performance is achieved only after two or three complete charge and discharge cycles!

2.3.1 Remove and install the battery

Follow the steps to remove the battery: ①slide down the back cover; ②lift the battery slightly and release it.

➤ Diagram3

Follow the steps as below to install the battery: ①Lock the battery in the slot ②slide upwards the back over until it is in the place.

➤ Diagram4

➤ 2.3.2The battery charges

➤ Plug in the charger

➤ Insert the connector of charger on the side of the mobile(Note that the arrow sign is facing upwards)

➤ At this moment, the power indication on the top of the right screen will flash in circle. If the mobile is switched off when is in charge, the charging icon is shown on the screen to indicate that the battery is in the process of charging. If your mobile is out of juice but it is still excessively in use, it takes some time to show up the charging icon while charging.

➤ When the power indication on the top of the right screen is full and not flash anymore, it means the charging is finished. It takes about3 or 4 hours in charging. It is normal that the battery, mobile and charger is getting hotter during the charging.

➤ Unplug the AC receptacle with mobile and charger while finishing charging.

- *Attention:

- The phone must be placed in a ventilated place with the temperature between +5°C ~ +40°C. Use only charger provided by the manufacturer. It may take a risk while using unauthorized charger and it may break the rules of this mobile phone recognition and the terms of warranty
-
- While the phone is turned off automatically or the warning of out of juice occurs, you should charge your phone timely. The phone will be able to decrease the charging time if the power hasn't been used up.
- The phone stand-by and call time provided by manufacturer is based on the ideal working environment. Actually, the working time of the battery has changed according to the condition of the network, work environment and the way of use.
- Please ensure the battery has been installed while charging. The battery can't be taken out during the charging.
- Disconnect the charger, phone and power after charging is finished.
- If you don't disconnect the charger, power and phone in some period of time(Let's say 5 or 8 hours), the power has consumed to some degree and the phone will start charging again. We don't recommend this way to operate on your phone as the functions and life of the battery will be affected.

1.1Diagrams5

2.4 Switch the phone on

press and hold the power key/hang-up key to switch the phone on as well as switching the phone off.

If the phone is switched on but the SIM card is not inserted, the phone will remind you of inserting the card. After inserting the SIM card, the will automatically verify if this SIM card is valid.

And then the notice on the screen will be displayed in order as below:

Input PIN1 (if you already set up the SIM card password) (please refer 4.4.4.5 "Security Setting" to operate in detail)

After the SIM card decrypt successfully, the phone will be able to search the available network automatically. (Searching a network will be displayed on the screen) Once getting through the network, the name of the network provider will be displayed in the center of the screen. It means the phone is in the condition of stand-by and it is available.

*Note: Supposed "Emergency only" displayed on the screen, it means you are out of the network (you are out of reach). However, you still can use emergency call according to the signal of your phone.

Chapter 3 Basic Information

3.2

3.2.1 basic key

- left soft key : Carry out the designation in the left interface
- right soft key: Carry out the designation in the right interface
- Ok key 。 After select the menu to confirm, in phone book's menu press the key can dial-up, in standby mode press the go to the menu.
- Call key To make a call and answer an incoming call, in standby mode press the call key can quickly go to "dialed call" menu.
- End key To end call or reject the call; press this key long time to power off ; in other condition, press this key return to standby mode.
- direction key Used to performance up , left, right, down of move the cursor, and the user can set its shortcut key by oneself.
- Numeric Keys In the standby screen, these key used to dial-up; in the edit screen, these key used to input number or characters.
- music play/pause key In the standby screen, press the key can directly play mp3 music, press again to pause the music.
- music stop key In the standby screen, press the key stop the mp3 music.
- cancel key The key can cancel the previous word when edit and input.
- volume side key : 。 Used to control the volume size, in the second menu can used to up or down.
- photo side key Can go into camera directly.
- flashlight side key Can turn on/off the flashlight.

3.2.2 other shortcut key

contextual model shortcut key Click the first icon on the low of the left screen, can go into "contextual model" quickly.

- phone book shortcut key Click the second icon on the low of the left screen, can go to "short message" quickly.
- short message shortcut key Click the central icon on the low of the screen, can go into "call record".
- camera shortcut key Click the second icon on the low of the right screen, can go into "phone book" quick.
- Click the first on the low of right screen, can go into soft key.
- Click the central icon on the low of the screen, can open the dial-up soft key.
- 。 Click keypad lock sign 3 sec. on the screen. While turn on the lock, press the right soft key at first, and press can cancel key , can lock the keypad and the screen. while turn on the lock, press the right soft key at first ,and press cancel key or open the slippery cover.

Note: In this manual "press some key", means to pressing the key and then releasing it immediately; "keep pressing some key" means to pressing the key and keeping 2sec. or over 2 sec.

3.3Phone function

When the marking of network supplier appears on the screen, you can make a call or answer the calls. The signal stick on the left of the screen display the met work Signal Intensity(have 4 information line means to the signal is the strongest.) calls quality is influenced by barrier greater, so move a small scope can improve calls quality.

3.3.1 making calls

domestic telephone

Use the number buttons to enter the numbers, or click the dial-up icon on the low of the screen, click the number on the touch screen to making calls. If need modify the phone number, press right soft key delete input character. When you dial-up, the screen will show the animation. after the other party answers the phone , the screen will show the calls information, if open the connect warning tone, you can listen a warning tone (need network support)

Press END CALL button to hang up

zone letter +phone number +dial-up key

➤ dial-up telephone extension

some telephone can't dial-up directly, you need dial-up the telephone exchange at first, dial-up telephone extension number. When you input the phone number, insert the pause character "p" between telephone exchange number and telephone extension number, the mobile phone can complete the dial-up, automatically dial-up the telephone extension. The method of inputting "P" is keep pressing *key. (The screen will show the sigh "P" at the time)

zone letter +telephone exchange number +P +telephone extension number +dial-up key

➤ take example for pause character

for example :if you nave a dial-up way of voice mailbox system in number 888000 ,mailbox number is 6666, password is 8888, you can dial-up following the way.

The first part of the number used to dial-up the voice mailbox. After the call is answer, send 666 to select mailbox.(before the password is sent, the waiting for a telephone connect, the later P means that 5 sec. delay)

If you want to dial-up the international telephone ,keep pressing 0 key, until the screen show the prefix character "+" of the international telephone. This allow you do not know the phone prefix number in place (for example: in china is 00) to make calls in any country).

Input prefix number after, input the nation zone letter and phone number that you want to dial-up .nation zone letter is according to the usual practice, German is 49, England is 44, Sweden is 46 etc.

Like dial-up international telephone Usually ,dorp the "0" in the front of city zone letter when make calls.

:for example :dial-up customer service hotline in other country. Should call:

- If the mobile phone in the network overlay region. (you can view the network Signal Intensity. on top left corner of the screen) you should your network supplier didn't provide to travel extensively a service in that region, the screen will show "only emergency call", tell you only dial-up the type of call.

3.3.2 answer calls

Usually, To answer a call, press the CALL key

- If set open the any key to answer, you can key to answer calls.

- If the headphones already plug into, you can use the key on the headphones to answer calls. If you press key inconvenient, can open answer calls automatically setting, and the headphones already plug into, then after flapping bell or vibrating 5 sec , answer calls automatically.

3.3.3 reject calls

When an incoming call arrives, press the END CALL key to reject the call.

Chapter 4 Menu Introduction.

4.1 telephone directories

? Check to seek quickly: Choose this can enter telephone directory to browse interface, that window way provides a to check to seek the importation frame under, you can correspond an information in this importation frame under ,you can correspond an information in this importation to carry on the sieving of the telephone record. Can be provided to choose of check and seek the way have: 1. pronounce 2. The small letter of alphabet 3. Numeral. Can pass to click a screen central input method making to cut over an input method under to attain to seek a way to cut over.

? The name checks to seek: Press the name method to check to seek a record in the telephone directory.

? Add to numbered: Go toward to increase a new telephone record in the telephone directory, can choose the saving way as the SIM card or the cellular phone.

*Note: Both have a little bit differentiation on the saving format.

All replications: All records carry on a replication in the opponent machine or SIM card, canning choose from cellular phone to the SIM card, or coming to hand machine from the SIM card.

Deletion: Choose this deletion operation that carries out to the telephone .The choice deletes SIM card to record in all telephone from the SIM card; The choice deletes the cellular phone telephone directory to record in all telephone from the cellular phone; Choice's deleting item by item can carry on to the telephone record to delete an operation item by item.

Telephone a group of sets: This cellular phone provides fives to telephone for you a group of sets, you can carry on changing name, bell method, bell ring type and telephone to each set the picture and color, and cluster the characteristic enactment that constitute a member.

Other numbers: The other is a saving number in the SIM card, such as : This machine number, the service telephone with urgent number. You can carry on look into to it with the modification.

Constitution: The constitution function of the telephone directory. Is divided into five thin items: The capacity search, the storage position, name card constitution, my name card and telephone is thin to register.

- The capacity search: The usage circumstance information of the SIM card telephone directory and the cellular phone telephone directory.
- Store position : The choice has the initiative saving position , cellular phone or SIM cards.

- My name card: Edit detailed data of record the user.
- Telephone the big head stick: Choose the diagram mark that the customer telephone.
- Telephone bell ring: The customer can telephone differently from the choice bell ring.
- Telephone film: Customer can from choose the film that the dissimilarity telephone.

*Note : This cellular phone is saving 300 telephone numbers.

4.2 short news

4.2.1 Short news

accept a box : Information looked in to have already receive. Can press assurance after appearing to accept a short news row watch o box to read a detailed contents of news. Can press options to carry on a following operation at this time:

- Reply: Give at present short news of the dispatcher send out a message.
- Deletion: Delete at present short news.
- Editor: Withdraw the contents of the message, enter to edit a frame.
- Turn hair: Turn to deliver that short news.
- Make duplicate to the SIM card (cellular phone): If this news stores in hand machine in ,then make duplicate it to the SIM card. If this news storage then comes to hand its replication in the SIM card machine in.
- Move to the SIM card (cellular phone): If this news stores in hand machine in ,then move it to the SIM card . If this news stores in hand its ambulation in the SIM card machine in .
- Chat: Enter a chat room
- Delete all: The deletion accepts all short news in a box.
- The replication is all: Will store the all short news in the in hand machine to make duplicate the storage SIM card perhaps in the all short news replication in the SIM card come to hand the machine the storage.
- Move all: Will store the all shore news in the in hand machine to move SIM card perhaps in the all short news ambulation in the SIM card come to hand the machine the storage.
- Use number: Withdraw the cellular phone number of the dispatcher of that message, you can choose to carry on stiring number or keep it to the telephone directory to it.
- Store item: Withdraw the object in the short news, carry on a storage.
- Deliver a box: Information looked in to nave already send out. Can press assurance after appearing the hair piece the short news row watch of the box to read news detailed contents. Can press options to carry on a following operation at this time:
- Send out :Send out that short mewes. You can choose to send out in man ways or cluster the set send out to come to send out that short news at most person.
- Editor: Withdraw the contents of the current message, carry on editor.

- Deletion: Delete that short news.
 - Make duplicate to the SIM card duplicate it to the SIM card. If this news stores in hand machine in , then comes to hand its replication in the SIM card machine in .
 - Move to the SIM card(cellular phone): If this news store in hand machine in ,then move it to SIM card. If this mews storage then comes to hand its ambulation in the SIM card machine in.
 - Delete all: Delete the hair piece all short newses in box.
 - The replication is all: Will store the all short news in the in hand machine to make duplicate SIM card come to hand the machine the storage.
 - Move all : Will store the all short news in the in hand machine to move SIM card perhaps in the all short news ambulation in the SIM card come to hand the machine the storage.
 - Use number: Withdraw the cellular phone number that that message receives, you can choose to carry on stiring number or keep it to the telephone directory to it .
- Write a letter interest: Enter the submenu writes a message, can input short news.
- Completion: Choose this mean that message importation complete, can enter the next move operation.
1. Send out : Send out this information, choose this will enter the consignee editor frame, you can press the numerical key importation number, or press to check to seek to adjust a telephone directory, winning election to choose the other party number from the telephone directory, pressing assurance to send out.
 2. The conservancy erupts to send: Send out this information to deposit that news into the hair piece in the meantime box.
 3. Storage: Don't send out that short news, but deposit it into the hair piece box.
 4. Send out in many ways: Send out this short news to several cellular phone numbers.
 5. Cluster the set send out: Choose a cent set, send out this short news to all members in the cluster's set.
 - In common use and short language: Insert pre-established in common use and short language in this short news.
 - Insert object: Insert objects, such as picture, bell ring and animation...etc. in that short news.
 - Writing format: The writing that defines that short news edits a format.
 - Input method: Input method changed the message editor.

*Note: Parts of cities and the message center nonsupport of the regions are more than 70length newses of Chinese characteres(or 160 English character lists).

In common use and short language: Can write in some in common use sentences in the in common use information to repeat at the time of sending out

a message by avoid of knock to go into one by one .Can edit or delete.

The message establish: At the time of using short news function, you want to be the constitution of the necessity first.

- The mode establish: Choose a suitable mode for the cellular phone message. Enter each mode can to the name , message center number ,valid time, the message format constitution for correspond.
- The appearance establish: Establish whether open the news report or the reply path.
- The capacity search: Look into the SIM card or the cellular phone mailbox in of the space occupy a circumstance.
- Store position : Choose the cellular phone or SIM card.
- The short news transmission enactment: The short news delivers the choice of [with] way, the GPRS have the initiative, the GSM have the initiative, only usage GSM.

*Note: This function demand carries a camp a company a support.

4.2.2colorful messages

The colorful message includes a writing, picture harmony sound contents. Pass a multi-media information (colorful message) service(the Multimedia Messaging Service, MMS), you can not only send out or receive the picture and writing ,but also receive a supplementary orotund document of information, grasping the information that the contents enrich heartily. Colorful message's passing a colorful screen will bring a fresh and clear color with the lifelike audio-visual experience for you.

This cellular phone support receive biggest is the colorful message with 50 KBs, if the size of the colorful message exceeds restriction, the cellular phone won't can receive that information. The cellular phone support send out biggest is the colorful message with 50 KBs.

This cellular phone support is many page colorful messages, namely each contents of the page include a picture, a music and the writing contents, but the colorful message is constitute by many such pages. If include a picture in the colorful message. the cellular phone will adjust a picture to zoom automatically, making it show at the cellular phone screen up.

*Note: The function demand carries a camp a company a support.

Write a letter interest: Set up a colorful message lately. You can fill in consignee, copy to send, the topic, contents and enclosure.

Accept b box: Look in to receive a colorful message. (Concretely operate an of the same language origin a message in of accept b box)

- Look into: Look into a current colorful message.
- Information detail: Look into the detailed circumstance of the current colorful message, include an addresser, topic, date, time, size.
- Use number: Withdraw the number of the dispatcher of the current colorful message.
- The colorful message reply: Give the dispatcher of the current colorful message perhaps all addressers and consignee with colorful message of the

form reply.

- The message reply: Give the dispatcher of the current colorful message perhaps all addressers and consignee with message of the form reply.
- Turn hair: Send out the current colorful message to the another consignee.
- Receive: If this colorful message hasn't yet accept, then accepting it down.
- Break to open : Break to open to receive.
- Deletion: Delete a current colorful message.
- Delete all : The deletion accepts all contentses in a box .
- Deliver a box: Save to send out an unsuccessful and multi-media information. (Concretely operate an of the same language origin the hair piece within message a box)
- Look into: Look into a current colorful message.
- Information detail: Look into the detailed circumstance of the current colorful message, include consignee, date, time, size etc..
- Turn hair: Turn this colorful message to give ovt others.
- Send out: Re-send out a current colorful message.
- Break to open: Stop send out.
- Deletion: Delete a current colorful message.
- Delete all: The deletion accepts all contentses in a box .
- Preliminary draft box : The message editor completes behind if don't send out and can keep here. The information will turn to save to arrive to have already send out an information after send out.

- Look into : Look into a current colorful message contents.
- Information detail: Look into the detailed circumstance of the current colorful message, include consignee, date, time, size etc..
- Send out: Send out a current colorful message.
- Editor: Edit a current colorful message.
- Deletion: Delete a current colorful message.
- Delete all : Delete to have already send out medium of all contentses.
- Constitution: Establish the related parameter that the multi-media information sends out and receives.
- Send out a constitution: The colorful message send out of some related parameter constitution. Expect such as the usage inside, send out repay, read repay, priority, partition time, deliver time etc..
- Receive a constitution: The colorful message receives some related parameter constitutions in the process. Such as the main network, travel extensively a network, deliver the reading report and allow transmission a report etc..
- Filter a constitution: Filter parts of colorful messages.
- The network establish: The colorful message network constitution, include the colorful message center, the net pass, port, the network account number etc. constitution.
- Saving space: The number of the saving colorful message, the biggest

number, has already used informations, such as space and the surplus space...etc..

- Saving position: The saving position of the colorful message, the cellular phone saves card perhaps.

4.2.3 chat

Arbitrarily the function of the chat room is as follows:

The chat room set : Establish the telephone number of my pet name and the other party.

Start chat: Enter the chat room combines to start chat.

4.2.4 speech mailboxes

Arbitrarily the function in the speech mailbox is as follows:

Editor: Establish the name and telephone number.

Link to the speech: Stir the number links to the speech mailbox.

4.2.5 small area broadcast

Accept and reads the news that the small area broadcast, the function is as follows:

Receive mode: Open and closes the catcher whom the small area broadcast.

Read information: The reading has already receive of small area broadcast information.

Language: Choose language.

The channel establish: The channel constitution that the small area broadcast. Include a choice and add, edit with delete

4.3 converse record

Answer the phone: 20s that record a dissimilarity didn't answer the phone number.

Have already stired a telephone: Record a dissimilarity of 20 have already stirde telephone number.

Have already answer the phone : Record a dissimilarity of 20 have already answered the phone number.

At converse record the row form interface under, press assurance can look into the detailed information that should record, including date and stiring to beat time, name, number and stiring a dozen of number of times.

Can press options to carry on to the current telephone record choose to operate as follows under the detailed information interface.

- Deletion: Delete this record.
- Conservancy: Keep this number to the SIM card or the cellular phone.
- Sir number: Stir to make that telephone number call.
- Editor: Edit that telephone number combines to deposit it into the telephone directory.

Delete a converse record: Can choose pure empty a certain converse record row form.

Converse time: There are two submenu last times in conversely time converse time, have already stired a telephone to total, have already

answered the phone to total with all account return zero.

- Converse to account last time hour: Look into the last converse time.
 - Have already stired a telephone total: Look in to have already stived total time of telephone.
 - All account return zero: All converse to account return zero.
Converse charge: The converse expenses can be saving for you converse total amount charge.
 - Last time converse expenses: Look into the last converse expenses.
 - All converse expenses: Look into converse expenses of total amount.
 - The price and fee rate : Enter a converse fee rate of submenu, can browse, modification or cancel that function. Modify among them function to need importation PIN2codeses with the cancel.
 - The converse expenses return zero: Input PIN2codeses, can restart a charge towards accounting the price machine to carry on purely zeroth,.
- Attention: The part operation needs you to input PIN2codeses, please contact our network supplier with obtain that password.